

## Digital Thermometer WT-2

### Technical parameters:

- ◆ Temperature measuring range:  $-50^{\circ}\text{C} \sim +300^{\circ}\text{C}$  ( $-58^{\circ}\text{F} \sim +572^{\circ}\text{F}$ )
- ◆ Resolution:  $0.1^{\circ}\text{C}$
- ◆ Accuracy:  $\pm 1^{\circ}\text{C}$  ( $0^{\circ}\text{C} \sim 60^{\circ}\text{C}$ ),  $\pm 5^{\circ}\text{C}$  (other range)
- ◆ Power supply: DC1.5V, 7# Alkaline battery

### Features:

- ◆ Switch between  $^{\circ}\text{C}$  and  $^{\circ}\text{F}$
- ◆ Data holding
- ◆ Max. Min. temperature memory
- ◆ Max. Min. temperature setting and alarm

### Key description:

- ◆ ON/Off: Turn on/off the thermometer
- ◆ HOLD: Hold the measuring data
- ◆ SET: Alarming setting
- ◆ ADJ: Adjust the setting value
- ◆ AC: Cancel alarm
- ◆ MAX/MIN: Display Max. or Min. temperature
- ◆ OK: Save

### Operation instructions:

- ◆ [ON/OFF]: Press to turn on the thermometer then enter into the measuring mode.
- ◆ [SET]: Press to enter into alarm setting mode.
- ◆ [ADJ] and [OK]: Press "SET" to enter into alarm setting mode. Alarming high temperature "HI" flashes. Press [ADJ] to add  $1^{\circ}\text{C}$  and add it faster when pressing the key for more than 2 sec. The temperature returns to be  $1^{\circ}\text{C}$  higher than the alarming low temperature when exceeds  $300^{\circ}\text{C}$ . Press OK to save and enter into alarming low temperature setting. "LO" flashes. Adjust it as the same way. "AL" displays in alarming mode. Alarm sound lasts for 5 sec. and can be cancelled by press "AC".
- ◆ [AC]: Cancel alarm and enter into temperature measuring mode. "AL" disappears.

V1.1

						WT-2英文 说明书(常规)			JY-8.805.229		
标记	处数	分区	更改文件号	签名	年月日	阶段标记		重量	比例		
设计			标准化			S	A	-	1: 1		
校准			版本	V1.1		共 1 张			徐州精英电器技术有限公司		
审核			批准			第 1 张					
工艺											